

hal:on

by LEDBLADE



RGBW LED Halo Set for P1/P1 mini and light set mode

MAIN FEATURES

- 'hal:on basic set' for 'P1' retro lamp
- 'hal:on P1 mini' set / add-on for 'P1 mini'
- 'hal:on light set' for standalone function
- High brightness digital LED
- Direct power and signal to 'P1' and 'P1 mini' luminaire
- Daisy chain Ethernet
- Direct mode for pixel mapping
- Fixture mode for fast lighting application
- Built in effect engine
- Dual layer color mixing in fixture mode
- QMS „Quick Mount System“ for easy and quick assembly

ADD NEW GLORY TO YOUR EVENT LIGHTING!

SPECIFICATIONS

- No. of pixels: 146 (2 x 73) - RGBW 4000K
- Main input: 100-240 V @ 50-60 Hz
- Power consumption: 75W
- Connectors: RJ45, XLR, PowerCon in/out
- Control protocols: DMX 512, ArtNet, sACN
- Modes: *Fixture mode: 14 ch / *Direct mode: 584 ch
- Rating: indoor, IP 22
- Weight: 1.5 kg
- CE
- hal:on basic set contains:
 - 1 x RGBW LED ring 'halo' w/ fixing clamps (4); 1 x dark 'halo' cover;
 - 1 x hal:on controller unit; 1 x power cable + patch cable;
 - 1 x backplate 'Gibbon' for P1; 1 x spare set of fixing clamps
- Additional details and specifications for 'hal:on P1 mini' and 'hal:on light set' options available at www.ledblade.com/products/ or via info@ledblade.com